

Parameter identification of nonlinear time-dependent rubber bushings models towards their integration in multibody simulations of a vehicle chassis

Guillaume Puel, Béatrice Bourgeteau, Denis Aubry

▶ To cite this version:

Guillaume Puel, Béatrice Bourgeteau, Denis Aubry. Parameter identification of nonlinear time-dependent rubber bushings models towards their integration in multibody simulations of a vehicle chassis. Mechanical Systems and Signal Processing, 2013, 36 (2), pp.354-369. 10.1016/j.ymssp.2012.10.021. hal-00799243

HAL Id: hal-00799243 https://centralesupelec.hal.science/hal-00799243

Submitted on 11 Mar 2013 $\,$

HAL is a multi-disciplinary open access archive for the deposit and dissemination of scientific research documents, whether they are published or not. The documents may come from teaching and research institutions in France or abroad, or from public or private research centers. L'archive ouverte pluridisciplinaire **HAL**, est destinée au dépôt et à la diffusion de documents scientifiques de niveau recherche, publiés ou non, émanant des établissements d'enseignement et de recherche français ou étrangers, des laboratoires publics ou privés.

Parameter identification of nonlinear time-dependent rubber bushings models towards their integration in multibody simulations of a vehicle chassis

Guillaume Puel¹, Béatrice Bourgeteau, Denis Aubry

Laboratoire MSSMat, Ecole Centrale Paris / CNRS UMR 8579, Grande Voie des Vignes, 92290 Châtenay-Malabry, France

Abstract

Rubber bushings are extensively-used linking parts in a vehicle chassis that allow to filter noise and vibration. They influence much, however, the transient behaviour of the vehicle, such as its steering performance. Therefore building a multibody simulation with a relevant description of the rubber bushings is useful to describe the significant characteristics of the vehicle's steering behaviour. First, a nonlinear time-dependent model describing a rubber bushing's mechanical behaviour is presented. In order to be relevant, the parameters associated with this model are then identified from experimental tests using an adjoint state formulation of the identification problem. The identified values are eventually validated using additional experimental data.

Keywords: rubber bushings, nonlinear time-dependent model, parameter identification, adjoint state, multibody simulation

1 1. Introduction

Rubber bushings are mechanical parts that are extensively used to reduce noise and vibration in a vehicle chassis. They have, however, a strong impact on the whole vehicle chassis behaviour, such as its steering performance.

¹Corresponding author.

Preprint submitted to Mechanical Systems and Signal Processing

Email addresses: guillaume.puel@ecp.fr (Guillaume Puel),

beatrice.bourgetau@sagem.com (Béatrice Bourgeteau), denis.aubry@ecp.fr (Denis Aubry)

Since it is not always possible to get experimental data directly on the whole chassis system, their impact has to be described using a multibody simulation. This would include a relevant model of the rubber bushings mounted in the chassis. This paper focuses on the identification procedure that allows to determine the parameters associated with such a model. This will be done by means of experimental data derived from specific measurements on bushings mounted in test rigs.

The following provides an outline of the paper. First, the rubber bush-12 ings' behaviour enlightening the different phenomena to take into account 13 in the model is briefly presented. Then the characteristics of the chosen 14 model are given; two points are underlined: how relevant this choice is to 15 describe the observed phenomena, and how the results coming from the as-16 sociated multibody simulations allow to describe some qualitative, but sig-17 nificant characteristics of the vehicle's steering behaviour. In order to derive 18 more accurate, quantitative results from these simulations, the characteri-19 zation of the actual rubber bushings' behaviour is needed. Consequently, a 20 series of measurements on test rigs have been performed in conjunction with 21 several suppliers of bushings. These tests are primarily used as an experimen-22 tal reference in the identification procedure. This is the core of the study, 23 which is described in detail: a misfit function expressing the discrepancy 24 between the model's results and the experimental data is defined and then 25 minimized by means of a gradient-based minimization algorithm using an 26 adjoint state formulation. The identification results are eventually presented 27 and discussed. 28

²⁹ 2. Mechanical behaviour of the rubber bushings

³⁰ 2.1. Description of the mechanical part

Rubber bushings are cylindrical parts that consist of a metallic inner core and a plastic or metallic outer frame linked one to the other by a rubber intermediate body (Figure 1). The inner core and the outer frames are connected to different parts of the chassis.

The geometry of the rubber intermediate body is not exactly axisymmetric: pits and ribs allow distinct behaviours for different load directions. Thus the bushing's tridimensional mechanical behaviour can be split into several simple uniaxial behaviours, corresponding to classical types of loads (axial, radial, torsional, ...). These different behaviours can be described in a simple way, for they can be directly related to the material behaviour of



Figure 1: Typical rubber bushing

rubber. Thus in the following, the study of the mechanical characteristics
of rubber will be studied rather than the influence of the geometry of the
rubber intermediate body.

44 2.2. Material mechanical behaviour of rubber

Rubber usually exhibits three canonical components in its mechanical 45 behaviour: an elastic component, which is totally reversible, and two dissi-46 pating (thus irreversible) components, which are hysteresis and viscoelastic-47 ity. Additional specific effects also have to be taken into account. All these 48 behaviours have been listed in numerous references [1, 2, 3], which tried to 49 propose some associated simple models as the basis of more complex models. 50 The elastic component is characterized by a nonlinear stress versus strain 51 curve, which can be obtained from cyclic measurements involving high-amplitude 52 displacements at low speed: in this case, the irreversible effects can be ne-53 glected. If not, one way to derive the stress versus strain curve is to flatten 54 the obtained cycle into an average curve assumed to represent the elastic 55 component only. Furthermore, for rather small displacements, as it is gener-56 ally the case for the bushings typically used, the stress versus strain relation 57 can be considered as linear, or, at worst, as piecewise linear. 58

The hysteretic component is mainly due to the presence of carbon black as a reinforcing filler in rubber: inner friction-like phenomena due to these particles create a history effect, which depends on the loading speed. This
component is of utter importance for the vehicle chassis behaviour, especially
at small amplitudes where hysteresis is the most significant effect.

Carbon black particles also have an additional impact on the bushing's 64 secant stiffness, called the Payne effect [4]. The secant stiffness is considered 65 when plotting the force versus displacement curve as cyclic displacements 66 are applied to the bushing, and is defined as the slope of the secant line 67 joining the two extreme points of the obtained hysteresis cycle. For small 68 displacement amplitudes, the Payne effect consists in a secant stiffness that 60 decreases rapidly as the loading amplitude increases. This effect is significant 70 enough to be taken into account in the bushings typically used: it can be 71 seen in experimental measurements that the higher the proportion of carbon 72 black fillers, the stronger this effect. 73

Whereas hysteresis is often a rate-independent phenomenon, viscoelastic-74 ity on the contrary depends on the loading speed, and can be related to the 75 friction that takes place between the rubber macromolecules. The associated 76 effects are particularly significant in relaxation, which occurs when a displace-77 ment characterised by a Heaviside step function is applied to the bushing: 78 the force versus time curve depends on the amplitude of the displacement 79 step function as well as its speed (for the application of the displacement is 80 not truly discontinuous). Relaxation has to be taken into account because it 81 denotes an evanescent memory effect, which is crucial in the vehicle's steer-82 ing behaviour: two successive steering wheel rotations will not have the same 83 effect depending if they are in the same direction or in opposite directions. 84

Another significant impact of the viscoelastic component can be observed 85 in the frequency domain: there is a dynamic stiffening of the bushing as the 86 loading frequency increases. The bushing's dynamic stiffness is derived from 87 a first-harmonic analysis of the force obtained when a sinusoidal displacement 88 is applied to the bushing: it is defined as the amplitude ratio of the force's 89 (predominant) first harmonic to the displacement. This effect is opposed to 90 the Payne effect: even if it is more limited, it should be taken into account 91 in the bushing's model. 92

One last effect related to the mechanical behaviour of rubber should be evoked: the Mullins effect [5], which consists in a strong decrease in the bushing's secant stiffness occurring whenever the load increases beyond its prior all-time maximum value. After a few cycles at a given amplitude, it can then be assumed that the stiffness does not evolve any more, provided there is no applied load of higher amplitude. This damage-like effect, though ⁹⁹ significant, will not be taken into account here, for it is assumed that all the
^{bushings} which are used in the chassis are first exerted in a burn-in process:
¹⁰¹ they are submitted before operational service to various loads along different
¹⁰² directions, so that the Mullins effect is no longer significant once the bushings
¹⁰³ have been mounted on the chassis.

¹⁰⁴ 3. Mechanical model for the rubber bushings

Since the typical geometry of a rubber bushing is designed such that 105 the mechanical behaviours along the different directions are decoupled, the 106 geometry influence is not further studied, and a simple model can be proposed 107 for each loading mode. Furthermore, the model should be chosen as simple 108 as possible so that its implementation in a multibody simulation software 109 could be easy and robust. Therefore rheological models are used that have 110 to represent the different components described in Section 2.2. The degrees 111 of freedom (DOFs) associated with these models correspond to the nodes 112 linking the different rheological components. They are the solutions of the 113 Ordinary Differential Equations (ODEs) associated with the chosen models. 114

115 3.1. Standard Triboelastic Solid model (STS)

The Standard Triboelastic Solid model (STS), initially proposed by Coveney [6] 116 for seismic rubber bushings, is based on the linear superposition of a pure 117 elastic behaviour (described by a spring element) and a hysteretic component 118 (described by a solid friction element): the resulting combination, depicted 119 in Figure 2, is the STS elementary cell, whose combination in series can rep-120 resent a typical hysteretic cycle, for the different friction elements allow to 121 reproduce the desired memory effect. The parameters associated with the 122 STS elementary cell are the stiffness K_r of the spring element and the thresh-123 old force F_f of the friction element, which means that the friction element 124 slides if and only if the norm of the load acting on it is higher than the 125 specified threshold F_f . 126

Eventually, the proposed STS model, shown in Figure 3, is based on the serial combination of several identical STS elementary cells, along with two additional springs, K_0 and K_{pa} , standing for a global elastic stiffness and an additional stiffness for low-amplitude displacements respectively. The STS elementary cells are chosen identical for the sake of simplicity. Consequently, the proposed STS model is based on four distinct parameters, for the number



Figure 2: STS elementary cell

of STS elementary cells can generally be set once and for all. This number,
indeed, allows a more or less fine discretization of the hysteresis cycle.



Figure 3: STS model with N identical STS elementary cells

Although the STS model is able to represent the hysteretic component of the rubber bushing, it does not account for viscoelasticity. To take it into account, most current models add in parallel to the STS model elements with viscoelastic behaviour. For example, a Maxwell cell (*i.e.* viscous damping) is added in parallel in [7], but it generally seems difficult to suit the bushing's global dynamical response: [8] shows that using a viscous damping tends to entail an overestimation of the efforts in play.

¹⁴² 3.2. Rate-dependent Triboelastic model (RT)

Rather than add other components to the previous model, a better solution seems to replace the friction elements of the STS model by components exhibiting a viscoelastic behaviour: this is the Rate-dependent Triboelastic model (RT), proposed by Coveney as well [7]. The RT elementary cell comprises a linear spring element with stiffness K_r and a nonlinear viscous dashpot put in parallel. The force versus velocity law of the dashpot is characterized by two parameters (C_0, α) such that:

$$F_k(t) = C_0 \operatorname{sign}(y'_k(t)) |y'_k(t)|^{\alpha} \tag{1}$$

where $F_k(t)$ is the force applied on the dashpot and $y'_k(t)$ is the velocity of the corresponding DOF. α is chosen such that $0 < \alpha < 1$: depending on this value, the dashpot exhibits different behaviours. In particular, if $\alpha = 0$, the dashpot is exactly equivalent to the solid friction element used in the STS model (when $C_0 = F_f$).

Eventually, the proposed RT model is based on the serial combination of several identical RT elementary cells, along with two additional springs, K_0 and K_{pa} , standing for a global elastic stiffness and an additional elastic stiffness for low-amplitude displacements respectively. The RT elementary cells are chosen identical again for the sake of simplicity, resulting in the assembly depicted in Figure 4.

Since, once again, the number N of RT elementary cells is set a priori (allowing a more or less fine discretization of the hysteretic cycle), the proposed RT model depends on P = 5 distinct parameters: $\mathbf{p} = (K_0 K_{pa} K_r C_0 \alpha)^{\mathrm{T}}$. The forward problem thus consists in solving the following system of N timedependent ODEs:

$$(K_{pa} + K_r)y_1(t) - K_r y_2(t) + C_0 \operatorname{sign}(y'_1(t))|y'_1(t)|^{\alpha} = K_{pa}y_0(t)$$
(2)
$$\vdots -K_r y_{k-1}(t) + 2K_r y_k(t) - K_r y_{k+1}(t) + C_0 \operatorname{sign}(y'_k(t))|y'_k(t)|^{\alpha} = 0$$

$$\vdots -K_r y_{N-1}(t) + 2K_r y_N(t) + C_0 \operatorname{sign}(y'_N(t))|y'_N(t)|^{\alpha} = 0$$

for 1 < k < N. The different DOFs $(y_k(t))_{1 \le k \le N}$ are the components of the state vector $\mathbf{y}(t)$, whereas $y_0(t)$ is the prescribed displacement. It is also assumed that the initial conditions for each DOF are equal to zero.



Figure 4: RT model with N identical RT elementary cells

169 3.3. Other models

In addition to these two previous models, numerous models relying on 170 alternative choices of rheological components have been proposed and exten-171 sively studied. For example, a fractional derivative model can be introduced 172 in the viscoelastic part [9]. This kind of model, used in [10] along with a gen-173 eralized friction force element, allows to accurately account for the evolutions 174 of the dynamic stiffness of rubber isolators as the frequency and amplitude 175 of the excitation, as well as the static precompression, evolve. This model, 176 however, seems hardly suited to be implemented in a multibody simula-177 tion, because most of the associated algorithms used to solve the fractional 178 derivative part in the time domain are rather sophisticated [11], or can be 179 very time-consuming. Furthermore, the parameter identification seems far 180 more awkward in the time domain than in the frequency domain. 181

Another widely-used model coming from [12] then [13] is the Bouc-Wen model consisting in a parametric hysteretic loop along with a spring and a linear viscous dashpot in parallel. The identification of the parameters associated with this model has been achieved in [14] in the frequency domain using a harmonic balance approximation. Used as is, however, the Bouc-Wen model exhibits some inconsistencies when compared with experimental data, and tends to overestimate the rate-independent hysteretic part relatively to

the rate-dependent part. Several modifications have been introduced to im-189 prove the model, such as in [15] recently: the proposed model consists in 190 two simple Bouc-Wen models put in parallel along with a spring and a linear 191 viscous dashpot. Even if this modified Bouc-Wen model gives better predic-192 tions of the bushing's behaviour, it depends on 16 independent parameters. 193 This makes the parameter identification rather difficult: in [15], a genetic 194 algorithm is proposed, but the identified values of the different parameters 195 strongly depend on the experimental data used in the identification process, 196 because the inverse problem is significantly ill-posed due to the high number 197 of parameters. The authors then propose to combine several experimental 198 test results to improve the identification, but the process eventually seems 199 to be delicate to apply. 200

²⁰¹ 3.4. Simulations examples using the RT model

Considering the conclusions of the previous section, the RT model seems 202 to be the most relevant choice. First the number of RT cells has to be set 203 so that the predictions are sufficiently refined to be similar to the curves 204 obtained with the available measurements. Typically N can be directly re-205 lated to the discretization of hysteresis cycles as far as the simulation of 206 quasistatic periodic displacements is concerned: Figure 5 shows the hys-207 teresis cycles obtained for different values of N. The different parameters 208 $\{K_0, K_{pa}, K_r, C_0, \alpha\}$ have been chosen such that the simulated cycles have 209 similar features, *i.e.* the same values of the maximum load, the secant stiff-210 ness, and the tangents before and after cusps. For N > 10, the obtained 211 curves have converged to a limit cycle whose smoothness seems satisfactory. 212 Finally, N = 15 cells are chosen to be able to account for applied displace-213 ments which would be larger than the ones proposed in the measurements, 214 which could possibly happen in the vehicle chassis in operation. 215

In Figure 6, different simulations using the proposed RT model with 216 N = 15 elementary cells are depicted and show the model's ability to grasp 217 most of the effects described in Section 2.2. On the left of Figure 6, the 218 force-displacement curves, obtained when sinusoidal displacements are ap-219 plied to the bushing, are plotted: they clearly show the bushing's stiffening as 220 the loading frequency increases. More precisely, the secant stiffness, defined 221 as the ratio between the maximum load and the maximum displacement, 222 increases by 4% between 1Hz and 10Hz, and by 4.5% between 10Hz and 223 100Hz. On the right of Figure 6, one shows the force obtained when a dis-224 placement described by a Heaviside step function is applied to the bushing: 225



Figure 5: Numerical simulations obtained with the RT model for different numbers of cells

relaxation is clearly observed, until the force goes down to a given constant value, consistent with the bushing's static behaviour and the value of the applied steady-state displacement. In the same way, it is possible to verify that the proposed RT model is able to account for the Payne effect as well.



Figure 6: Numerical simulations obtained with the RT model for different prescribed displacements: sines of increasing frequencies (left) and Heaviside step function (right)

230 3.5. Implementation in a multibody simulation code

The RT model has then been implemented in a multibody simulation of a typical chassis using ADAMS software. More precisely, user functions programmed in Fortran allow to compute the load associated with the chosen
model when a given displacement is applied to the rubber bushing.

Two different strategies are available. Using a GSESUB user function 235 allows to solve the ODEs associated with the RT model along with the re-236 maining equations associated with the whole multibody system. On the 237 contrary, when a VARSUB user function is used, one has to implement di-238 rectly in the subroutine the time integration algorithm. These two strategies 239 have been tested on the very simple model of a beam linked to the ground 240 by a rubber bushing whose mechanical behaviour is described by the RT 241 model. They lead to similar results in terms of simulation results and ac-242 curacy. Nevertheless the VARSUB function seems to have more advantages 243 than the GSESUB function: it is possible to implement any time integration 244 scheme, independently from the one used for the remaining elements of the 245 structure, and the computation time tends to be shorter. The final choice 246 has then consisted of an explicit Euler scheme defined in the VARSUB func-247 tion. The time step is chosen accordingly to the variable time step used by 248 ADAMS, by dividing this latter by a given factor, which allows to guarantee 249 the stability of the Euler time integration scheme. 250

Different simulations have been run on a complete multibody model of a typical small family car using RT models for the rubber bushings mounted in the front and rear axles of the vehicle. Only two specific results are shown here, and are associated with one specific rubber bushing, mounted in the rear axle, as depicted in Figure 7. This rubber bushing, which links the rear crossbeam to the body, allows to filter vertical vibrations as well as to transmit longitudinal forces to the axle.



Figure 7: Location of one specific rubber bushing in the rear axle (partial view of the multibody model of a typical small family car)

A first simulation focuses on how the studied bushing behaves when an 258 angle characterised by a Heaviside step function is applied to the steering 259 wheel of the vehicle (actually, the angular input is not truly discontinuous, 260 but is characterised by a short time interval of constant angular velocity). 261 Figure 8 shows the radial horizontal load in the bushing with respect to time 262 in two different cases, depending on whether a RT model or a STS model 263 is used to describe the rubber bushing's behaviour. The two curves are 264 normalised by the respective maximum load values, which allows to easily 265 compare the two models. This comparison stresses the lack of relaxation 266 when using the STS model, whereas the RT model is able to account for this 267 effect, as expected. 268



Figure 8: Normalised load in the bushing with respect to time (angular Heaviside step function on the steering wheel): RT model (red) and STS model (black)

A second simulation allows to represent well-known phenomena in the 260 steering behaviour such as the evanescent memory effect. On the right of 270 Figure 9 the (normalised) load acting on the studied bushing is shown, when 271 two successive rotations (each described by a Heaviside step function) are 272 applied to the vehicle's steering wheel. This kind of input is inspired from 273 classical elk tests, consisting in avoiding an obstacle without braking and then 274 coming back to the right lane. Depending on whether these two rotations 275 are of the same direction or occur in opposite ways (as formally depicted on 276 the left of Figure 9), the load acting on the bushing can be very different: 277 the relaxation effect is stronger in the second case. This has an impact 278

on the toe and camber angles of the wheel associated with the bushing of interest. Similar results can be obtained for other bushings, allowing to conclude on the impact on the vehicle's steering behaviour, which is a wellknown phenomenon described by test drivers.



Figure 9: Normalised load during the second of two successive rotations of the vehicle's steering wheel: (blue) rotations of the same direction (pink) rotations of opposite directions (a positive rotation is equivalent to a left turn of the steering wheel)

The previous examples then demonstrate the relevance of the results pre-283 dicted by the multibody simulation. However, without experimental data, 284 which would be directly measured on the whole vehicle on the track, these 285 predictions remain essentially qualitative. In order to turn these results into 286 quantitative predictions, the next step consists in finding the correct values 287 for the RT model's parameters. Since experimental information is available 288 for each rubber bushing (coming from specific measurements in test rigs), the 289 values of these parameters should be identified so that the response of a bush-290 ing, which is calculated using the RT model under a given loading mode, fits 291 best the experimental measurements obtained with the same loading mode. 292

²⁹³ 4. Generic formulation of the identification problem

For the sake of clarity, the identification problem as it is defined and solved is first presented in a generic way. The parameter identification of the RT model of rubber bushings is developed in the next section.

²⁹⁷ 4.1. Generic formulation of the identification problem

The forward problem (2) associated with the RT model can be described by the following implicit vector formulation of size N:

$$\mathcal{F}(\mathbf{y}(t), \mathbf{y}'(t), \mathbf{p}, t) = \mathbf{0} \quad \forall t \in [0, T]$$
(3)
$$\mathbf{y}(0) = \mathbf{0}$$

where \mathbf{p} of size P and \mathbf{y} of size N are, just as before, the parameter vector and 300 the state vector comprising all the DOFs of the forward model respectively. 301 For the identification problem, it can then be assumed that the exper-302 imental data will be compared with quantities derived from the different 303 DOFs of the forward problem by means of a projection operator denoted \mathbf{A} , 304 of size $n \times N$, where n is the number of experimental measurements. Simi-305 larly, it is assumed that the experimental data can be written as if they were 306 derived from an experimental state vector of size N: this assumption has no 307 other consequence than allowing a clearer presentation of the identification 308 problem. Eventually, a so-called misfit function is defined, which expresses 309 the discrepancy between the n measurements $Ay_{exp}(t)$ and the n associated 310 quantities derived from the model $\mathbf{Ay}(t; \mathbf{p})$: 311

$$\mathcal{J}(\mathbf{p}) = \frac{1}{2} \int_0^T |\mathbf{A}(\mathbf{y}(t;\mathbf{p}) - \mathbf{y}_{exp}(t))|^2 \, \mathrm{d}t + \frac{1}{2} |\mathbf{R}(\mathbf{p} - \mathbf{p}_0)|^2 \qquad (4)$$

where $\mathbf{y}(t; \mathbf{p})$ is the solution of the state equation (3) calculated with parameters \mathbf{p} . Since the forward problem is nonlinear, it seems relevant to use a time formulation of the misfit function, hence the integral over time.

The last term of the misfit function is a norm introduced to regularize the inverse problem, by expressing that the sought parameters \mathbf{p} should be close to a vector \mathbf{p}_0 of typical values, with \mathbf{R} a diagonal operator whose values are to be set. This so-called Tikhonov's regularization term aims at reducing the ill-posedness of the identification process by bounding the magnitude of the sought parameters.

321 4.2. Minimization of the misfit function

The identification problem consists in minimizing the misfit function (4) to find the parameters allowing the model to be as close to the experimental data as possible. This minimization is usually performed by means of gradient-based techniques, where the derivative of $\mathcal{J}(\mathbf{p})$ is analytically introduced using an adjoint state problem. This method was described in [16], which deals with the identification of elastoplastic constitutive laws, whose form is quite similar to the kind of law used in the RT model.

The solution $\mathbf{z}(t)$ of this adjoint state problem can be considered as a Lagrange multiplier introduced in the following Lagrangian function $\mathcal{L}(\mathbf{y}, \mathbf{p}, \mathbf{z})$:

$$\mathcal{L}(\mathbf{y}, \mathbf{p}, \mathbf{z}) = \frac{1}{2} \int_0^T |\mathbf{A}(\mathbf{y}(t) - \mathbf{y}_{exp}(t))|^2 dt + \frac{1}{2} |\mathbf{R}(\mathbf{p} - \mathbf{p}_0)|^2 \qquad (5)$$
$$- \int_0^T \mathcal{F}(\mathbf{y}(t), \mathbf{y}'(t), \mathbf{p}, t)^{\mathrm{T}} \mathbf{z}(t) dt - \mathbf{y}(0)^{\mathrm{T}} \mathbf{z}(0)$$

where $(\mathbf{y}, \mathbf{p}, \mathbf{z})$ are considered independent and $(\cdot)^{\mathrm{T}}$ is the transposition. Minimizing the misfit function $\mathcal{J}(\mathbf{p})$ where \mathbf{y} verifies (3) is then equivalent to writing the first-order stationarity conditions for $\mathcal{L}(\mathbf{y}, \mathbf{p}, \mathbf{z})$. This can be clearly seen when expressing the first-order stationarity condition with respect to \mathbf{z} :

$$-\int_0^T \mathcal{F}(\mathbf{y}(t), \mathbf{y}'(t), \mathbf{p}, t)^{\mathrm{T}} \delta \mathbf{z}(t) \,\mathrm{d}t - \mathbf{y}(0)^{\mathrm{T}} \delta \mathbf{z}(0) = 0$$
(6)

for any admissible $\delta \mathbf{z}(t)$. This expression is actually the weak formulation of the state equation (3).

338 4.3. Adjoint state problem

When writing the first-order stationarity condition for $\mathcal{L}(\mathbf{y}, \mathbf{p}, \mathbf{z})$ with respect to \mathbf{y} , the following relation is obtained:

$$\int_{0}^{T} \delta \mathbf{y}(t)^{\mathrm{T}} \left(\mathbf{A}^{\mathrm{T}} \mathbf{A}(\mathbf{y}(t) - \mathbf{y}_{exp}(t)) \right) \mathrm{d}t$$
(7)
$$- \int_{0}^{T} \left(\nabla_{\mathbf{y}} \mathcal{F} \delta \mathbf{y}(t) + \nabla_{\mathbf{y}'} \mathcal{F} \delta \mathbf{y}'(t) \right)^{\mathrm{T}} \mathbf{z}(t) \mathrm{d}t - \delta \mathbf{y}(0)^{\mathrm{T}} \mathbf{z}(0) = 0$$

for any $\delta \mathbf{y}(t)$ verifying null initial conditions. $\nabla_{\mathbf{y}} \mathcal{F}$ and $\nabla_{\mathbf{y}'} \mathcal{F}$ stand for the directional derivatives of \mathcal{F} with respect to \mathbf{y} and \mathbf{y}' respectively. After integrating by parts, the previous weak formulation leads to the following expression:

$$\int_{0}^{T} \delta \mathbf{y}(t)^{\mathrm{T}} \Big(\mathbf{A}^{\mathrm{T}} \mathbf{A}(\mathbf{y}(t) - \mathbf{y}_{exp}(t)) \Big) \, \mathrm{d}t \quad (8)$$
$$- \int_{0}^{T} \delta \mathbf{y}(t)^{\mathrm{T}} \Big(\nabla_{\mathbf{y}} \mathcal{F}^{\mathrm{T}} \mathbf{z}(t) - \left(\nabla_{\mathbf{y}'} \mathcal{F}^{\mathrm{T}} \mathbf{z}(t) \right)' \Big) \, \mathrm{d}t - \delta \mathbf{y}(T)^{\mathrm{T}} \nabla_{\mathbf{y}'} \mathcal{F}^{\mathrm{T}} \mathbf{z}(T) = 0$$

which is equivalent to the following strong formulation defining the adjoint state problem:

$$\nabla_{\mathbf{y}} \mathcal{F}^{\mathrm{T}} \mathbf{z}(t) - \left(\nabla_{\mathbf{y}'} \mathcal{F}^{\mathrm{T}} \mathbf{z}(t) \right)' = \mathbf{A}^{\mathrm{T}} \mathbf{A}(\mathbf{y}(t) - \mathbf{y}_{exp}(t)) \quad \forall t \in [0, T] \quad (9)$$
$$\nabla_{\mathbf{y}'} \mathcal{F}^{\mathrm{T}} \mathbf{z}(T) = \mathbf{0}$$

The adjoint state problem is classical [16] and consists in solving for $\mathbf{z}(t)$ a linear time-backward ODE along with final conditions.

349 4.4. Optimality conditions for the parameters

Once the adjoint state problem is solved, the gradient of the misfit function with respect to \mathbf{p} can be evaluated. Because of the equivalence between the constrained minimization of $\mathcal{J}(\mathbf{p})$ and the stationarity of $\mathcal{L}(\mathbf{y}(t;\mathbf{p}),\mathbf{p},\mathbf{z}(t))$, it can be written that:

$$\nabla_{\mathbf{p}} \mathcal{J}(\mathbf{p}) = \nabla_{\mathbf{p}} \mathcal{L}(\mathbf{y}(t;\mathbf{p}),\mathbf{p},\mathbf{z}(t)) = \mathbf{R}^{\mathrm{T}} \mathbf{R}(\mathbf{p}-\mathbf{p}_{0}) - \int_{0}^{T} \nabla_{\mathbf{p}} \mathcal{F}^{\mathrm{T}} \mathbf{z}(t) \,\mathrm{d}t \quad (10)$$

and should be equal to zero at optimality. This is equivalent to say that the optimal parameters depend on a weighted time average of the derivative of the state equation (3) with respect to the parameters vector **p**, multiplied by the solution of the adjoint state problem (9).

The minimization problem eventually consists in solving three ODEs with 358 unknowns $(\mathbf{y}(t), \mathbf{z}(t), \mathbf{p})$: the forward problem (3), the adjoint problem (9) 359 and the optimality equation (10) set equal to zero. The straightforward 360 solution is not possible here, as the adjoint problem is time-backward: a 361 staggered process is then proposed instead, where the forward and adjoint 362 problems are solved successively on the one hand, and the optimality equation 363 on the other hand is used to derive successive estimates of the misfit function 364 gradient. These estimates are used in a classical gradient-based optimization 365 algorithm, such as a line-search or a trust-region method. In addition, for 366 the solution of the adjoint state problem, a change of variable for the time is 367 first introduced in order to solve a time-forward problem along with initial 368 conditions, rather than the original time-backward problem. 360

In terms of computational cost, evaluating the gradient of the misfit function is cheaper and more robust using the adjoint state formulation than with a finite difference formula. Whenever evaluating the gradient associated with P parameters, the finite difference formula requires the solutions of P additional forward problems, each one being evaluated with the same parameters as the computed forward problem, except for one parameter which is slightly perturbed in order to derive the corresponding component of the misfit function gradient. In addition, the computation of an integral is required for each of these P forward solutions, in order to evaluate the associated misfit function.

On the contrary, when using the adjoint state formulation, only one ad-380 ditional ODE (9) has to be solved, and since this ODE is formally close to 381 the forward problem, the solution of the adjoint state problem has the same 382 cost as the solution of the forward problem. Then the computation of an 383 integral is needed for each component of the gradient. To conclude, for each 384 step of the staggered process, only two ODEs have to be solved and N inte-385 grals have to be evaluated when using the adjoint state formulation, whereas 386 P+1 ODE solutions and N integrals evaluations are required with the finite 387 difference formula. 388

³⁸⁹ 5. Parameter identification of the RT model

³⁹⁰ 5.1. Formulation of the identification problem

The parameter identification is achieved according to the formulation presented in the previous section. Similarly to (4), the misfit function quantifies the discrepancy between the computed and measured forces when a specific displacement is prescribed to the bushing:

$$\mathcal{J}(\mathbf{p}) = \frac{1}{2} \int_0^T |K_0 y_0(t) + K_{pa}(y_0(t) - y_1(t; \mathbf{p})) - F_{exp}(t)|^2 dt \quad (11) + \frac{1}{2} |\mathbf{R}(\mathbf{p} - \mathbf{p}_0)|^2$$

where $F_{exp}(t)$ is the measured force, $\mathbf{R} = \text{diag}(R_{K_0}, R_{K_{pa}}, R_{K_r}, R_{C_0}, R_{\alpha})$ comprises the different regularization parameters to be set, and typical values for the different parameters are in $\mathbf{p}_0 = \left(K_0^0 \ K_{pa}^0 \ K_r^0 \ C_0^0 \ \alpha^0\right)^{\mathrm{T}}$.

The adjoint state formulation used for evaluating the misfit function gradient consists in solving the following time-backward equations:

$$(K_{pa} + K_r)z_1(t) - K_r z_2(t) - C_0 \alpha |y_1'(t; \mathbf{p})|^{\alpha - 1} z_1'(t)$$
(12)
$$-C_0 \alpha (\alpha - 1) \operatorname{sign}(y_1'(t; \mathbf{p})) y_1''(t; \mathbf{p}) |y_1'(t; \mathbf{p})|^{\alpha - 2} z_1(t) = -K_{pa}(F(t; \mathbf{p}) - F_{exp}(t))$$

$$\vdots$$

$$-K_r z_{k-1}(t) + 2K_r z_k(t) - K_r z_{k+1}(t) - C_0 \alpha |y_k'(t; \mathbf{p})|^{\alpha - 1} z_k'(t)$$

$$-C_{0}\alpha(\alpha-1)\operatorname{sign}(y'_{k}(t;\mathbf{p}))y''_{k}(t;\mathbf{p})|y'_{k}(t;\mathbf{p})|^{\alpha-2}z_{k}(t) = 0$$

$$\vdots$$

$$-K_{r}z_{N-1}(t) + 2K_{r}z_{N}(t) - C_{0}\alpha|y'_{N}(t;\mathbf{p})|^{\alpha-1}z'_{N}(t)$$

$$-C_{0}\alpha(\alpha-1)\operatorname{sign}(y'_{N}(t;\mathbf{p}))y''_{N}(t;\mathbf{p})|y'_{N}(t;\mathbf{p})|^{\alpha-2}z_{N}(t) = 0$$

for 1 < k < N, with vanishing final conditions, and where the force applied on the bushing, as evaluated by the RT model, is $F(t; \mathbf{p}) = K_0 y_0(t) + K_{pa}(y_0(t) - y_1(t; \mathbf{p}))$. The gradient of the misfit function then comprises all the following partial derivatives:

$$\nabla_{K_0} \mathcal{J} = \int_0^T y_0(t) (F(t; \mathbf{p}) - F_{exp}(t)) dt + R_{K_0}^2 (K_0 - K_0^0)$$
(13)

$$\nabla_{K_{pa}} \mathcal{J} = \int_0^T (y_0(t) - y_1(t; \mathbf{p})) (F(t; \mathbf{p}) - F_{exp}(t) + z_1(t)) dt + R_{K_{pa}}^2 (K_{pa} - K_{pa}^0)$$

$$\nabla_{K_r} \mathcal{J} = -\int_0^T (y_1(t; \mathbf{p}) - y_2(t; \mathbf{p})) z_1(t) dt - \int_0^T (-y_{N-1}(t; \mathbf{p}) + 2y_N(t; \mathbf{p})) z_N(t) dt$$

$$-\sum_{k=2}^{N-1} \int_0^T (-y_{k-1}(t; \mathbf{p}) + 2y_k(t; \mathbf{p}) - y_{k+1}(t; \mathbf{p})) z_k(t) dt + R_{K_r}^2 (K_r - K_r^0)$$

$$\nabla_{C_0} \mathcal{J} = -\sum_{k=1}^N \int_0^T \operatorname{sign}(y_k'(t; \mathbf{p})) |y_k'(t; \mathbf{p})|^\alpha z_k(t) dt + R_{C_0}^2 (C_0 - C_0^0)$$

$$\nabla_\alpha \mathcal{J} = -\sum_{k=1}^N \int_0^T C_0 \operatorname{sign}(y_k'(t; \mathbf{p})) \ln |y_k'(t; \mathbf{p})| |y_k'(t; \mathbf{p})|^\alpha z_n(t) dt + R_\alpha^2 (\alpha - \alpha^0)$$

This computed gradient is to be used within two classical minimization 404 algorithms: a line-search method and a trust-region method [17]. The first 405 results, however, are very unsatisfactory: the computed gradient is clearly 406 erroneous, and can even, in some cases, return infinite values. Further inves-407 tigations allowed to determine that this came from the viscoelastic law (1)408 used in the RT model: depending on the value of α and due to the oc-409 currences of the sign and absolute value functions, this law can be nearly 410 discontinuous, so that its derivative with respect to the velocity can be ex-411 tremely high for very small velocities. Furthermore, since $\alpha < 1$, the adjoint 412 problem (12) is singular when one of the velocities y'_k is equal to zero. This 413 analysis is corroborated by the results of [18], which shows that it is impossi-414 ble to derive the correct misfit function gradients when discontinuities occur 415

in the equations to solve, with errors of a magnitude independent of the time
step size. The authors then propose to smooth the discontinuities, and show
that the correct gradient values can be evaluated when the time step size is
'sufficiently small' in comparison with the smoothing parameter.

Therefore, in order to smooth the solved equations, we replaced the occurrences of the sign and absolute value functions by the following expressions
respectively:

$$\operatorname{sign}_{s}(y') = \frac{2}{1 + e^{-sy'}} - 1$$

$$|y'|_{s} = \frac{2}{s} \ln\left(1 + e^{sy'}\right) - y'$$
(14)

where s is a constant to set: the lower s is, the smoother the functions sign_s and $|\cdot|_s$ are. The first function is actually a classical sigmoid function, and the second one is the primitive function of the first one: this allows to directly replace the sign and absolute value functions by their smoothed counterparts in Equations (2), (12) and (13). The influence of the smoothing parameter s is depicted in Figure 10. To determine the best value for s, the accuracy of the adjoint state solution has to be determined.



Figure 10: Influence of the smoothing parameter s: smoothed sign function (left) and smoothed absolute value function (right)

430 5.2. Validation of the adjoint state solution

⁴³¹ A classical way to check the accuracy of the computed adjoint state is ⁴³² to use the mathematical property of the adjoint state equation (9), whose operator \mathcal{G} should be the adjoint of the operator associated with the differentiated forward state equation $\nabla_{\mathbf{y}} \mathcal{F}$. The idea is to solve the following equations, for any arbitrary vector **a**:

$$\nabla_{\mathbf{y}} \mathcal{F} \mathbf{b} = \mathbf{a} \tag{15}$$
$$\mathcal{G} \mathbf{c} = \mathbf{b}$$

Since theoretically one has $\nabla_{\mathbf{y}} \mathcal{F}^{\mathrm{T}} = \mathcal{G}$, the following equality should hold, provided the adjoint state has been correctly solved:

$$\mathbf{a}^{\mathrm{T}}\mathbf{c} = \mathbf{b}^{\mathrm{T}}\mathbf{b} \tag{16}$$

This dot-product test should be verified for different values of **a** to be positively sure that the adjoint state solution is correctly calculated.

A series of numerical tests were conducted in order to determine the most 440 relevant value that should be chosen for the smoothing parameter s. Using 441 an arbitrary set of parameter values $\mathbf{p}_{exp} = \left(K_0^{exp} K_{pa}^{exp} K_r^{exp} C_0^{exp} \alpha^{exp}\right)^{\frac{1}{2}}$ 442 in Equation (2) to simulate an experimental reference, the misfit function 443 (with no regularization term) and its gradient are evaluated for a given set 444 of parameters whose values are quite different from the experimental ones: 445 $(K_0^{exp}/2 \ 2K_{pa}^{exp} \ K_r^{exp}/2 \ C_0^{exp}/2 \ 2\alpha^{exp})^{\mathrm{T}}$. The results in the case of different 446 values of s (as well as without any smoothing) are listed in Table 1. In 447 addition, the dot-product test (16) has been applied for $\mathbf{a} = (1 \cdots 1)^{\mathrm{T}}$ and 448 the associated results are listed in Table 1 as well. 449

Smoothing	\mathcal{J}	$\nabla_{K_0} \mathcal{J}$	$\nabla_{K_{pa}} \mathcal{J}$	$\nabla_{K_r} \mathcal{J}$	$\nabla_{C_0} \mathcal{J}$	$ abla_lpha \mathcal{J}$	$\mathbf{a}^{\mathrm{T}}\mathbf{c}$	$\mathbf{b}^{\mathrm{T}}\mathbf{b}$
s = 0.1	921 787.149	-4752.446	-16.3299	-277.728	49 467.59	$-13\ 149.70$	$0.021\ 569$	0.021 576
s = 1	888 192.640	$-4\ 665.399$	-17.630	-268.873	$67\ 022.15$	$-13\ 154.49$	$0.021 \ 378$	$0.021 \ 351$
s = 10	888 192.739	$-4\ 665.399$	-17.735	-285.087	$38\ 570.69$	$-11 \ 927.34$	$0.028\ 785$	$0.020\ 740$
s = 100	888 192.736	$-4\ 665.399$	$-5.6\cdot10^9$	$-8.2 \cdot 10^{9}$	$-1.3 \cdot 10^{13}$	$1.2 \cdot 10^{12}$	$> 3 \cdot 10^7$	$0.020 \ 359$
none	888 192.736	$-4\ 665.399$	infinite	infinite	infinite	infinite	infinite	$0.020\ 245$

Table 1: Evaluation of the misfit function and its gradient, and dot-product test for different smoothing settings

As predicted, the dot-product test is more and more accurately verified as the smoothing increases, that is as s decreases. Other values of **a** give similar results. The best value for the smoothing seems to be s = 1, for it represents a trade-off between the correct estimation of the misfit function \mathcal{J} (and of its gradient) and the validation of the adjoint state characterized by the dot-product test.

In Table 2, we compare the directional derivatives previously computed 456 with s = 1 with those estimated with a finite-difference formula and no 457 smoothing. Even if the estimates are of the same order of magnitude, some 458 differences can be noticed, excepted for $\nabla_{K_0} \mathcal{J}$ where z is not used. On 459 the one hand, the computed problems are slightly different because of the 460 smoothing; on the other hand, the estimates which are computed using a 461 finite-difference formula without smoothing can not be considered as refer-462 ences, for they depend on the discretisation step used in the formula and 463 the smaller this discretisation step, the stronger the impact of the tolerance 464 of the forward state solution on the result of the formula. All in all, using 465 some smoothing and estimating the misfit function gradient by means of the 466 adjoint state seems to be relevant to solve the identification problem, as can 467 be seen in the following section. Eventually, the value s = 1 is used in what 468 follows. 460

Method	$ abla_{K_0}\mathcal{J}$	$ abla_{K_{pa}}\mathcal{J}$	$ abla_{K_r}\mathcal{J}$	$ abla_{C_0}\mathcal{J}$	$ abla_lpha \mathcal{J}$
adjoint state with smoothing	$-4\ 665.399$	-17.630	-268.873	67 022.15	$-13\ 154.49$
finite diff. without smoothing	$-4 \ 665.399$	-6.7776	-241.145	$39\ 672.53$	$-8 \ 141.242$

Table 2: Evaluation of the misfit function gradient

470 5.3. Identification results with synthetic data

In order to assess the accuracy of the identification process, preliminary 471 tests using synthetic data are proposed. Since actual experimental data come 472 from imposed quasistatic periodic inputs as well as Heaviside step functions, 473 it seems relevant to study similar inputs to quantify the accuracy of the 474 identification results. The final choice here is to compute the response to 475 sinusoidal displacements, and use them as synthetic data for the identification 476 process. Figure 6 (left) shows the typical curves that can be obtained for such 477 inputs. Synthetic data are computed using an arbitrary set of parameter 478 values $\mathbf{p}_{exp} = \left(K_0^{exp} K_{pa}^{exp} K_r^{exp} C_0^{exp} \alpha^{exp}\right)^{\mathrm{T}}$ in the forward problem (2), for 470 a sinusoidal displacement input of 1Hz-frequency. 480

Two different gradient-based algorithms, proposed in the Optimisation Toolbox for Matlab, are tested: a line-search method, consisting in a Quasi-Newton method with the BFGS formula for the approximation of the Hessian matrix [17], and a trust-region method, based on the interior reflective Newton method [19]. Identification results for both methods and close initial values $(K_0^{exp} 4K_{pa}^{exp}/3 2K_r^{exp}/3 2C_0^{exp} 2\alpha^{exp})^{\mathrm{T}}$ are listed in Table 3. They range from satisfactory to excellent depending on the parameter, and tend to be better with the trust-region method.

Method	$\frac{K_0}{K_0^{exp}}$	$\frac{K_{pa}}{K_{pa}^{exp}}$	$\frac{K_r}{K_r^{exp}}$	$\frac{C_0}{C_0^{exp}}$	$\frac{\alpha}{\alpha^{exp}}$
line-search	1.099	1.095	0.649	0.972	1.524
trust-region	1.001	0.975	0.767	1.270	0.922

Table 3: Identification results for synthetic data and initial values close to the 'experimental' ones

In order to check the robustness of the identification process, initial values 489 much farther from the values used for computing the synthetic data are 490 proposed: $(2K_0^{exp} 5K_{pa}^{exp} K_r^{exp}/5 C_0^{exp}/5 5\alpha^{exp})^{\mathrm{T}}$. They lead to the results 491 listed in Table 4. The results are far worse than in the case of initial values 492 chosen close to the 'experimental' ones. This means that there are many local 493 minima in the misfit function, making the identification process difficult as 494 is. In addition, some parameters, such as C_0 and α , seem not to have a 495 strong impact on the response, for the bushing is loaded in a quasi-static 496 way. Despite this final remark, it can be concluded that, between the two 497 methods, the trust-region method gives the best results. 498

Method	$\frac{K_0}{K_0^{exp}}$	$\frac{K_{pa}}{K_{pa}^{exp}}$	$\frac{K_r}{K_r^{exp}}$	$\frac{C_0}{C_0^{exp}}$	$\frac{\alpha}{\alpha^{exp}}$
line-search	1.328	5.121	0.227	0.498	7.954
trust-region	1.300	2.960	0.361	0.499	4.884

Table 4: Identification results for synthetic data and initial values far from the 'experimental' ones

To go further, some regularization is then required. It is not, however, 499 straightforward when dealing with the actual experimental data: since the 500 model uses rheological elements, there are no typical values which can eas-501 ily be chosen for the vector $\mathbf{p}_0 = \left(K_0^0 \ K_{pa}^0 \ K_r^0 \ C_0^0 \ \alpha^0\right)^{\mathrm{T}}$. Moreover, there is 502 actually no quantitative information available concerning the measurement 503 noise corrupting the experimental data. Applying principles such as Moro-504 zov's [20] in order to set relevant values for the regularization parameters 505 contained in **R** is then not really possible. With these two drawbacks, the 506

resulting regularization may not be relevant; therefore, rather than applying
a classical Tikhonov's regularization in the identification process, a technique
is proposed in the following section to give a first guess of the initial values
to be used in the minimization algorithm.

511 5.4. Determination of relevant initial values for the identification process

Due to the ill-posedness of the identification problem, it is crucial to 512 be able to give relevant initial values to the minimization algorithm in or-513 der not to converge to a local minimum which would lie too far from the 514 global one. This can be done by using the STS model described in Sec-515 tion 3.1 rather than the RT model, because the STS model can be analyti-516 cally inverted under some simple assumptions. Starting from the experimen-517 tal hysteresis curve, it is possible to get values for the associated parameters 518 $\mathbf{p}_{STS} = \left(K_0^S \ K_{pa}^S \ K_r^S \ F_f\right)^{\mathrm{T}}$. Then, initial values for the RT model's parame-519 ters can be derived from these parameter values. 520

First, it is assumed that all the STS cells but one (*i.e.* N-1 cells) are loaded when the hysteresis curve is obtained: this is equivalent to assume that the bushing is loaded with a sufficiently high-amplitude displacement. In this case, three representative features of the hysteresis curve can be determined as functions of the STS parameters $\mathbf{p}_{STS} = \left(K_0^S K_{pa}^S K_r^S F_f\right)^{\mathrm{T}}$:

• the secant stiffness associated with the two extremities of the hysteresis $_{527}$ cycle (with N odd):

$$K_{\rm sec} = K_0^S + \frac{K_{pa}^S K_r^S}{\frac{N-1}{2} K_{pa}^S + K_r^S}$$
(17)

• the slope of the line being tangent to the hysteresis cycle just after a cusp:

$$T_{\rm g1} = K_0^S + K_{pa}^S \tag{18}$$

the slope of the line being tangent to the hysteresis cycle just before a cusp:

$$T_{g2} = K_0^S + \frac{K_{pa}^S K_r^S}{(N-1)K_{pa}^S + K_r^S}$$
(19)

These features are summarized on Figure 11. Finally, the maximal force F_{max} applied on the bushing when N - 1 STS cells are loaded can be written as follows:

$$F_{\max} = K_0 \left(\frac{F_f N(N-1)}{K_r^S} + \frac{2F_f N}{K_{pa}^S} \right) + 2NF_f$$
(20)

This maximal force is obtained for a displacement amplitude X_{max} , which means that $F_{\text{max}} = K_{\text{sec}}X_{\text{max}}$.



Figure 11: Features of the hysteresis curve associated with the STS model

The previous formulas can be reversed in order to determine the STS parameters $\mathbf{p}_{STS} = \left(K_0^S K_{pa}^S K_r^S F_f\right)^{\mathrm{T}}$, for example in terms of slopes before and after a cusp, and maximal force and displacement :

$$K_0^S = \frac{F_{\max}(T_{g1} + T_{g2}) - 2T_{g1}T_{g2}X_{\max}}{2F_{\max} - (T_{g1} + T_{g2})X_{\max}}$$
(21)

$$K_{pa}^{S} = \frac{(T_{g1} - T_{g2})(F_{max} - T_{g1}X_{max})}{2F_{max} - (T_{g1} + T_{g2})X_{max}}$$
(22)

$$K_r^S = -\frac{(N-1)(T_{g1} - T_{g2})(F_{max} - T_{g1}X_{max})(F_{max} - T_{g2}X_{max})}{(2F_{max} - (T_{g1} + T_{g2})X_{max})^2}$$
(23)

$$F_f = \frac{(F_{\max} - T_{g1}X_{\max})(F_{\max} - T_{g2}X_{\max})}{N(2F_{\max} - (T_{g1} + T_{g2})X_{\max})}$$
(24)

If it is assumed that the STS and RT models are roughly similar, the first three expressions can give straightforward initial values for the first three RT ⁵⁴² model's parameters:

$$K_0^0 = K_0^S \quad K_{pa}^0 = K_{pa}^S \quad K_r^0 = K_r^S \tag{25}$$

In order to determine estimates for the last two, it is assumed that the viscoelastic part (1) of the RT cell should be analogous to the threshold force F_f of the STS cell when the bushing is loaded at a (mean) speed V_0 , that is:

$$C_0^0 = \frac{F_f}{V_0^{\alpha^0}}$$
(26)

To remain quite close to the solid friction behaviour of the STS cell, an arbitrary choice of a small value for α^0 is made, such as one tenth or one fifth.

This strategy has been tested on the example from the previous section. 550 In Table 5 are listed the initial values of the RT model's parameters that 551 are obtained from the synthetic hysteresis cycle when two different values 552 of α^0 are proposed. The obtained values show some discrepancies with the 553 'experimental' ones: it can be explained by the fact that the slopes T_{g1} and 554 T_{a2} cannot be determined without some error and that any inaccuracy in the 555 associated values can have a strong impact on the determination of the STS 556 model's parameter values. As an example of this sensitivity, Figure 12 shows 557 how the first three STS model's parameters evolve as the measured value of 558 the slope T_{g2} varies: the changes can go up to nearly 100% for a 10%-change 559 in the value T_{g2} . As any other inverse problem, the quality of the inversion 560 of the formulas associated with the STS model shows a strong dependence 561 on the noise in the measurements. 562

α^0	$\frac{K_0^0}{K_0^{exp}}$	$\frac{K_{pa}^0}{K_{pa}^{exp}}$	$\frac{K_r^0}{K_r^{exp}}$	$\frac{C_0^0}{C_0^{exp}}$
1/10	0.770	1.105	1.468	0.703
1/5	0.770	1.105	1.468	0.740

Table 5: Initial RT model's parameter values using an STS model identification and the synthetic hysteresis cycle

All these results, however, show that it is possible to get reasonable initial values for the RT model's parameters: all the proposed values lie in a range of the same magnitude as the one proposed in the first identification example with synthetic data (with associated results in Table 3). Moreover, the



Figure 12: Normalized values of the first three STS model's parameters with respect to the slope T_{g2} measured on the hysteresis curve

arbitrary choice of a value for α^0 does not seem to have too high an impact on the proposed value for C_0^0 . Finally, since all these values are perturbed by some noise, it seems better, as stated previously, to use them as initial values for the minimization algorithm rather than nominal values in a Tikhonov's regularization term such as the one proposed in (11). The resulting benefit should be the minimization algorithm to likely start in the attraction basin of the global minimum of the misfit function.

574 5.5. Identification results from actual data

As described previously, actual experimental data come from quasistatic 575 periodic as well as fast transitory loads, applied to the bushing by means of 576 a specific test rig. Two simple test configurations are proposed: the first one 577 consists in applying to the bushing a triangular periodic displacement at a 578 rather limited speed and is used in the identification process. The second 570 configuration consists in applying a displacement characterised by a Heav-580 iside step function to observe relaxation in the bushing (the input being 581 not truly discontinuous, but being characterised by a 0.1s time interval of 582 increase): but rather than using the associated measurements in the iden-583 tification process as well, one prefers to keep them as a further reference in 584 order to validate the identified model a posteriori. 585

The same gradient-based algorithms as in Section 5.3 are used here. Ini-586 tial values of the RT model's parameters are given according to the strategy 587 described in Section 5.4; since the experimental curve (depicted in Figure 13) 588 or 14) is not perfectly symmetric, an average value of each feature has been 589 used. Table 6 lists the (relative) identified values of the RT model's param-590 eters as well as a normalized value of the discrepancy between the model's 591 results and experimental data: this value is calculated as the square root 592 of the final misfit function divided by a norm \mathcal{J}_0 of the experimental data, 593 defined by the following expression: 594

$$\mathcal{J}_{0} = \frac{1}{2} \int_{0}^{T} |F_{exp}(t)|^{2} \,\mathrm{d}t$$
(27)

This normalized value is a good guess of the relative identification error. Whereas this error was equal to 15.32% with the proposed initial values, it drops significantly for the values identified with the two methods. Eventually, the two methods lead to very similar results, even if the line-search method seems to provide a slightly better solution.

Method	$\frac{K_0}{K_0^0}$	$\frac{K_{pa}}{K_{pa}^0}$	$\frac{K_r}{K_r^0}$	$\frac{C_0}{C_0^0}$	$\frac{\alpha}{\alpha^0}$	$\sqrt{\frac{\mathcal{J}}{\mathcal{J}_0}}$
line-search	1.217	1.049	1.088	0.930	1.197	3.11%
trust-region	1.182	1.145	1.156	0.889	1.153	3.20%

Table 6: Identification results for actual data (triangular periodic displacement)

Figures 13 and 14 (left) show for each method the comparison between 600 the experimental data and the responses associated with the initial RT model 601 and with the identified RT model. As seen previously with the relative 602 errors, the agreement is very good in the case of the triangular periodic 603 loading. Let us note that only the stabilised hysteresis curves are recorded 604 in these quasistatic tests: no information is available on the first loading 605 of the bushing. This latter is mandatory in the numerical simulation: it 606 is introduced by considering that a linearly-varying displacement is applied 607 to the bushing: afterwards, the stabilised hysteresis cycle is obtained. The 608 misfit function is based on these experimental and predicted stabilised cycles 609 only. 610

Validation of these results is possible with the experimental response to the Heaviside step function, which has not been used in the identification ⁶¹³ process. Figures 13 and 14 (right) show the good agreement between the ⁶¹⁴ response associated with the identified RT model and the experimental data. ⁶¹⁵ Since these latter have not been used in the identification process, this result ⁶¹⁶ shows the relevance of the RT model as well as the quality of the identification ⁶¹⁷ of the associated parameters. In particular, both the relaxation phenomenon ⁶¹⁸ and the asymptotic steady-state load are well described by the identified ⁶¹⁹ model, when compared with the experimental data.



Figure 13: Identification results with the line-search method: comparison with the experimental data used (left) and with experimental data not used in the identification process (right)



Figure 14: Identification results with the trust-region method: comparison with the experimental data used (left) and with experimental data not used in the identification process (right)

620 6. Conclusion

Here a strategy for identifying the parameters of a nonlinear time-dependent model has been presented and applied on the example of a rubber bushing typically used in car chassis. The proposed model is based on components exhibiting a viscoelastic behaviour which can tend towards the description of contact-type phenomena. The identification has been achieved in the time domain using an adjoint state formulation allowing an efficient estimation of the misfit function's gradient.

It was shown that the near-discontinuous behaviour of the proposed model can lead to numerical difficulties, which may prevent the model's parameters to be correctly identified due to an inaccurate estimation of the adjoint state variable. The solution has consisted in smoothing the discontinuities by means of sigmoid functions: a trade-off allowed to correct the estimates of the adjoint state without any significant loss of accuracy for the forward state solution.

The relevance of the proposed model as well as the robustness of the method have been shown with the parameter identification from actual data: in addition, the obtained results have been validated with experimental information which was not used in the identification process. Such an identification allows to deal with accurate models, which are simple enough to be implemented in multibody simulation softwares, allowing to study wellknown phenomena occurring in a typical vehicle chassis.

In a more general way, the strategy presented here can be applied to other time-dependent problems with contact-type phenomena, and should allow to achieve the parameter identification both accurately and efficiently.

⁶⁴⁵ 7. Acknowledgements

The authors would like to acknowledge the support of PSA Peugeot 647 Citroën for this study.

648 References

- [1] A. Lion, A constitutive model for carbon black filled rubber: experimental investigations and mathematical representation, Continuum Mechan-
- ics and Thermodynamics 6 (1996) 153–169.

- [2] C. Miehe, J. Keck, Superimposed finite elastic-viscoelastic-plastoelastic
 stress response with damage in filled rubbery polymers. Experiments,
 modelling and algorithmic implementation, Journal of the Mechanics
 and Physics of Solids 48 (2000) 323–365.
- [3] P. Haupt, K. Sedlan, Viscoplasticity of elastomeric materials: experimental facts and constitutive modelling, Archive of Applied Mechanics
 71 (2001) 89–109.
- [4] A. R. Payne, A note on the existence of a yield point in the dynamic
 modulus of loaded vulcanizates, Journal of Applied Polymer Science
 3 (7) (1960) 127.
- [5] L. Mullins, Softening of rubber by deformation, Rubber Chemistry and
 Technology Journal 42 (1969) 339–362.
- [6] V. A. Coveney, D. E. Johnson, D. M. Turner, A triboelastic model for
 the cyclic mechanical behavior of filled vulcanizates, Rubber Chemistry
 and Technology Journal 68 (1995) 660–670.
- [7] V. A. Coveney, D. E. Johnson, D. M. Turner, Rate-dependent modeling
 of a highly filled vulcanizate, Rubber Chemistry and Technology Journal
 73 (4) (2000) 565–577.
- [8] U. Tornar, Application of strain integral damping to engine mounts, in:
 P. Sas, M. De Mucnck (Eds.), ISMA 2006 International Conference
 on Noise and Vibration Engineering, Leuven, Belgium, 2006, pp. CD–
 ROM.
- [9] R. L. Bagley, P. J. Torvik, Fractional calculus a different approach
 to the analysis of viscoelastically damped structures, AIAA Journal 21
 (1983) 741–748.
- [10] M. Sjöberg, L. Kari, Nonlinear isolator dynamics at finite deformations: an effective hyperelastic, fractional derivative, generalized friction
 model, Nonlinear Dynamics 33 (2003) 323–336.
- [11] J.-F. Deü, D. Matignon, Simulation of fractionally damped mechani cal systems by means of a Newmark-diffusive scheme, Computers and
 Mathematics with Applications 59 (2010) 1745–1753.

- [12] R. Bouc, Modèle mathématique d'hystérésis, Acustica 24 (1971) 16–25.
- [13] Y. K. Wen, Method of random vibration of hysteretic systems, ASCE
 Journal of the Engineering Mechanics Division 102 (1976) 249–263.
- [14] Y. Q. Ni, J. M. Ko, C. W. Wong, Identification of non-linear hysteretic
 isolators from periodic vibration tests, Journal of Sound and Vibration
 217 (4) (1998) 737–756.
- [15] J. K. Ok, W. S. Yoo, J. H. Sohn, New nonlinear bushing model for gen eral excitations using Bouc-Wen hysteretic model, International Journal
 of Automotive Technology 9 (2) (2008) 183–190.
- [16] A. Constantinescu, N. Tardieu, On the identification of elastoviscoplastic
 constitutive laws from indentation tests, Inverse Problems in Science and
 Engineering 9 (1) (2001) 19–44.
- ⁶⁹⁵ [17] J. Nocedal, S. J. Wright, Numerical Optimization, 2nd Edition, ⁶⁹⁶ Springer, 2006.
- [18] D. E. Stewart, M. Anitescu, Optimal control of systems with discon tinuous differential equations, Numerische Mathematik 114 (4) (2010)
 653–695.
- [19] T. F. Coleman, Y. Li, On the convergence of reflective Newton methods
 for large-scale nonlinear minimization subject to bounds, Mathematical
 Programming 67 (2) (1994) 189–224.
- [20] V. A. Morozov, Methods for solving incorrectly posed problems,
 Springer, 1984.